

Como criar uma OT ativada por evento?

help.fracttal.com/hc/pt-pt/articles/24948207103885-Como-criar-uma-OT-ativada-por-evento

As tarefas com triggers tipo evento são executadas apenas como tarefas não planeadas, tendo diferentes formas de lidar com esse evento. Para isso, primeiro é necessário gerar uma tarefa não planeada (a partir de qualquer uma das opções disponíveis) e selecionar um ativo associado a um plano de tarefas que contenha tarefas ativadas por evento.

The screenshot displays the Fracttal Work Management interface in Kanban view. The top navigation bar includes a hamburger menu, 'Work Management', 'View Kanban', and user profile 'JC'. The main area is divided into four columns:

- Pending Tasks (168 items):** Contains three task cards. The first card is for 'Asset: HOYO 18 { GRU-AV-G03-CG1-HY18 }' with task 'LIMPIEZA Y CORTE', scheduled for 02:00 on 2025-03-28, with a frequency of 'EVERY 1 DAY(S)'. The second card is for 'Asset: HOYO 15 { GRU-AV-G03-CG1-HY15 }' with task 'LIMPIEZA Y CORTE', scheduled for 02:00 on 2025-03-28, with a frequency of 'EVERY 1 DAY(S)'. The third card is for 'Asset: PROCESO { PROC-01 }' with task 'EVALUACIÓN DE EQUIPO', scheduled for 00:10 on 2025-03-26, with a frequency of 'EVALUACION DE EQUIPO'. The fourth card is for 'Asset: (Robus-2) INOVA TP 924' with task 'FALLA DETECTADA', scheduled for 00:10 on 2025-03-25, with a frequency of 'UNPLANNED'.
- WOs in Process (2744 items):** Contains three task cards. The first card is for 'OT-43-GR' created by ALEXANDER SANCHEZ, with assets 2 and work management 2, task 'INSPECCION DE FUGAS', scheduled for 04:00 on 2025-03-27, with a frequency of 'Multiple assets'. The second card is for 'OT-39-GR' created by Diego Vergara, with asset '(EQ.ECV-00) GENERADOR', task 'CAMBIAR PARABRISA', scheduled for 00:30 on 2025-03-26, with a frequency of 'VICTOR SILVA'. The third card is for 'OT-38-GR' created by JOSÉ FERNANDO CRUZ MOSQUEDA, with asset '(AGRO-TRAC-001) TRACTOR 1', task 'INSPECCION DE FUGAS', scheduled for 00:10 on 2025-03-26, with a frequency of 'Miguel Mosqueda'.
- WOs in Review (215 items):** Contains three task cards. The first card is for 'OT-35-GR' created by ALEXANDER SANCHEZ, with asset '(TRAC-ALEX-01) TRACTOR ALEXANDER', task 'INSPECCION DE FUGAS', scheduled for 00:10 on 2025-03-28, with a frequency of 'Abelardo Perez'. The second card is for 'OT-24-GR' created by JOSÉ FERNANDO CRUZ MOSQUEDA, with asset '(COMP-01) COMPRESOR RECIPROCANTE 01 ZHONGHE 250 KG', task 'No enciende máquina', scheduled for 00:30 on 2025-03-25, with a frequency of 'Miguel Mosqueda'. The third card is for 'OT-18-GR' created by ALEXANDER SANCHEZ, with asset 'bomba diesel 01 { }', task 'INSPECCIÓN ANUAL PREVIO PRUEBA', scheduled for 00:10 on 2026-03-21, with a frequency of 'Juan Pablo Hidalgo'.
- Closed WOs (2424 items):** Contains three task cards. The first card is for 'OT-42-GR' created by ALEXANDER SANCHEZ, with asset 'HOYO 18 { GRU-AV-G03-CG1-HY18 }', task 'LIMPIEZA Y CORTE', scheduled for 02:00 on 2025-03-27, with a frequency of 'Alexander Sanchez'. The second card is for 'OT-41-GR' created by Jonas Campos, with asset '(ROB-0001) ROBO - 0001', task 'Asset Review', scheduled for 00:30 on 2025-03-27, with a frequency of 'Jonas Campos'. The third card is for 'OT-40-GR' created by Jonas Campos, with asset 'Fracttal (ACT.LOC-0001)', task 'ANALISE DE EQUIPO', scheduled for 20:00 on 2025-03-27, with a frequency of 'Jonas Campos'. The fourth card is for 'OT-36-GR' created by Jonas Campos, with asset '(ROB-0001) ROBO - 0001', task 'Lectura', scheduled for 00:10 on 2025-03-26, with a frequency of 'Jonas Campos'. A red box highlights a blue plus icon in the bottom right corner of the 'Closed WOs' column.

← Non Scheduled Tasks

1 Asset 2 Task 3 Sub Tasks 4 Resources

Asset

Asset can't be blank

Incident date 2025-03-27 15:14 Requested By Jonas Campos

☐ Has the asset failed?

Next >

← Non Scheduled Tasks

1 Asset 2 Task 3 Sub Tasks 4 Resources

Asset

Asset can't be blank

Incident date 2025-03-27 15:17 Requested By Jonas Campos

☐ Has the asset failed?

Next >

← Q ACT.LOC-0001 X

8

Fractal { ACT.LOC-0001 }

Type: Locations

Code: ACT.LOC-0001

Priority: Low

Location: //

Showing 1 of 1

Ao fazer isso, o sistema exibirá uma nova janela com todas as tarefas ativadas por eventos para esse ativo, nesse caso existem 3 maneiras de lidar com este evento:

Asset related events: Fracttal { ACT.LOC-0001 }



1 2

Event

Task



falla del motor

Falla de motor eléctrico

Showing 1 of 1

- 1. Lançar Evento:** Esta opção permite executar a tarefa como se fosse uma tarefa planeada de um plano de tarefas. Ao lançar o evento, esta tarefa aparecerá no módulo de tarefas pendentes (a data de programação será a mesma data em que o evento foi lançado).
- 2. Trazer os dados da tarefa selecionada:** Esta opção permite executar a tarefa com todos os detalhes adicionados ao plano (como se o evento fosse lançado), mas como uma tarefa não planeada. Além disso, esta opção também permite editar os detalhes da tarefa sem afetar o plano de manutenção associado.
- 3. Omitir:** Esta ação permite gerar uma OT não planeada a partir do zero. Ou seja, é possível registar uma OT que não tenha relação com nenhum dos eventos associados a esse ativo.

Após definir como lidar com o evento, basta seguir o procedimento habitual para gerar a OT associada à tarefa em questão e finalizar o processo.